



WiJET.Video

QUICKSTART GUIDE

Included with the WiJET.Video

- Quickstart Guide
- WiJET.Video Wireless Projector and Monitor Adaptor
- 5V DC Power Adapter & Cord
- Antenna
- WiJET.Video CD-ROM with Application Software and Technical Manual
- Registration Card

Step 1: Connecting WiJET.Video Physically

- A.** Connect the VGA cable from either a projector or a monitor to the VGA port at the rear of the WiJET.Video. Turn on the projector or monitor.
- B.** Connect the included 5V DC power adapter into the port labeled 5V at the rear of the WiJET.Video. The ON LED will turn solid amber. At the end of a brief "boot up" period, WiJET.Video displays a banner page through its connected projector/monitor.
- C.** The WiJET.Video is now awaiting an 802.11b/g radio to connect to it. When the LINK LED located on the front of the WiJET.Video blinks amber, the unit is ready for connection to a PC.

Step 2: Installing Software

- A.** Insert the provided WiJET.Video installation CD-ROM. The auto installation program allows you to either run the WiJET.Video software from the installation CD without installation or install the WiJET.Video software to your PC.

Step 3: Configuring your PC for WiJET.Video

- A.** Take note of the WiJET.Video SSID displayed at the top left of the banner page.
- B.** Follow the manufacturer's instruction to configure your wireless 802.11b/g adaptor on your PC as a Station and in Infrastructure mode. From the list of active radios found by the radio, connect it to the AP with the same SSID as the WiJET.Video.
- C.** To enable network and Internet access while simultaneously connected to the WiJET.Video, you must have both your wireless adapter and the WiJET.Video connect to an existing access point which provides the Internet access. In this case, you need to change the WiJET.Video radio to operate in "Infrastructure Station" mode. See Step 6 on how to change the radio configurations of the WiJET.Video.

Step 4: Using WiJET.Video for Presentation

- A.** **For optimal performance, disable your PC's Video Hardware Accelerator.** From the Display Properties window, click on the "Settings" tab. Click on the "Advanced" button followed by the "Troubleshoot" tab. Move the slider for "Hardware acceleration" to none.
- B.** Double click the WiJET.Video shortcut icon on the desktop to start the **Presentation Session Manager (PSM)** if the software is installed or click the "Run from CD" button on the WiJET.Video Installation Utility window displayed by the auto installation program. Click the "OK" button on the message box displayed when the **PSM** first starts.
- C.** Click "Establish a Session" on the **PSM** to start a presentation session. The WiJET.Video will display your computer's desktop through the connected projector or monitor. The LINK LED turns solid green. You are now in session with the WiJET.Video!

Note: Your wireless device must have a valid IP address in order for the **PSM** to establish a session. A wireless device running DHCP may take a few moments to acquire a valid IP address. Please refer to the Technical Manual for more detail.

Step 5: Using PPT Launcher & Video Player

- A.** While the **PSM** is in session, click "PPT Launcher" to select a PowerPoint file for slide show. This feature must be used to play embedded videos in the chosen PowerPoint files.
- B.** Click "Video Player" to start Video Player dialog. Click "Open" to browse for the desired video file and use the standard controls to play the video. To return to the **PSM**, click "exit".

Step 6: Administering WiJET.Video

- A.** Follow Step 3 to configure your wireless adapter card. Follow Step 4 to run the **PSM** and connect with the WiJET.Video. Click on the WiJET.Video icon on the SysTray and select the menu item to show the connected WiJET.Video unit(s).
- B.** Select the unit to be administered and click on the "Admin" button. This launches your Web browser and accesses the WiJET.Video administrative facilities. To login, enter "admin" for user name and "public" for password.
- C.** Navigate the administrative web pages to customize the configuration of WiJET.Video unit.

Please consult the WiJET.Video **Technical Manual** for additional features and customization.

OTC Wireless, Inc. provides technical assistance to our customers.

For most current information, visit our website at

<http://www.otcwireless.com/>.

US support phone is (800) 770-6698.